

NEW 250-3357

NEW WIRING INSTRUCTIONS

1. To remove old switch push in on switch assembly rotate and remove. You may have to rotate back and forth for switch to come out
2. Route switch wiring down column before assembling the connector to plug.

CAUTION

3. Connectors are numbered on the bottom side. Pictures above denote wire location based on number and color.
4. Color Chart
 - i. Blue Wire Goes in Position 1
 - ii. Green Wire Goes In Position 2
 - iii. Red Wire Goes in Position 3
 - iv. Yellow Wire Goes in Position 4

